

CB-PRG/20 PROGRAMMER FOR CAN BUS 933-932 ALARM UNITS

The programmer, to be used in combination with the MATRIX software, must exclusively be used to update and configure CAN BUS 933/932 alarm units. The programmer must only be powered with a 12Vcc power supply.

The MATRIX software is available for download in the restricted area of our website www.gemini-alarm.com.

Do not reverse order of listed steps; it is mandatory to follow the connection sequence described here below.

ATTENTION: turn off the computer before carrying out electrical work.

1. Plug the CA0858 USB connector to the computer USB port.
2. Connect the BLACK wire clip (CA0858 wiring) to the negative pole and the RED wire clip to the positive pole of a 12V power source.
3. Plug the CA0833 wiring connectors into the alarm unit socket counterparts.
4. Connect together the 5-pin connectors of CA0858 and CA0833 wirings.
5. Power the system by switching the power supply ON.
6. Turn ON the computer.

ATTENTION: Possession and use of the programmer are strictly reserved to Authorized Users who shall not allow use or transfer possession to third parties unless explicitly authorized, in writing, by Gemini Technologies srl.

Gemini Technologies cannot be held responsible for possible damages caused by improper or erroneous use of the programmer.

CONNECTION DIAGRAM

